



*Televes reserves the right to modify the product*

## EasyF 6W Splitter 5...2400 MHz 11 dB/14 dB

6-way Splitter for SMATV signals, with a compact design and an efficient electrical behaviour.  
concieved for indoor installation, it can also be used outdoors with a case (ref. 4163).  
Supplied in 10-unit boxes.

**Ref.5469**

**Art.Nr**

EFV6

**EAN13**

8424450118986

### Highlights

- EasyF connection system: easy to install, savings on mounting
- Made of Zamak, high shielding
- Outstanding reliability: automated manufacturing using new generation micro-components

### Main features

- Improves through losses
- Outstanding electrical behaviour: impulsive noise reduction
- Grounding screw provided
- DC pass from the outputs to the input

### Discover

#### EasyF connection system: simplicity and savings

EasyF is an innovative connection concept where the inner conductor of the coaxial cable is directly inserted in the device, thus improving connection reliability. Thanks to the absence of F connectors, the chassis can be reduced and the connection of two cables secured with a a single screw.

- Real time savings: speeding the installation is possible without the need for coaxial cable termination.

Furthermore, there is no need for screwing the connectors on the device, which is sometimes difficult when there is little room

- Connection reliability: the clamp holding the cables prevents the coaxial cable to come off
- Cost savings: no additional connectors are required (neither F nor IEC)
- Space optimization: inputs and outputs are always on the same side of the device to prevent coaxial cables from bending, and to make working inside cabinets and register boxes easier
- Very easy three-step mounting: only screwing and unscrewing the covers is required to connect both cables:

1. Unscrew the device's cover to access the connection

2. Insert the previously stripped coaxial cables

3. Close the cover and screw to ensure connection

## Learn more about EasyF system reliability

With EasyF, the connection between the coaxial cable and the device is carried out using an automated system for contact insertion of the inner conductor, without any soldering.

- Always as new: the device's operating life increases when the factor of solder wearing out with time is removed
- Failure rate reduction: usually produced as a result of cold soldering joints
- Electromagnetic behaviour optimization: for high frequencies
- Our commitment with environment is reinforced: pollution caused by the welding process is eliminated and production power consumption is reduced

## Technical specifications

Frequency range	MHz	5 ... 2400			
Number of outputs		6			
Inputs/Bands			TERR	SAT	
##	dB		14	14	
Through losses W2	dB		14	14	
Through losses W3	dB		12	12	
Through losses W4	dB		12	12	
Through losses W5	dB		13	11	
Through losses W6	dB		13	11	
Rejection between outputs	dB		> 28	> 28	
Connectors		"EasyF" type			
Voltage max.	V	40			
Max. current	mA	300			
DC pass		Out□In			