



Televes reserves the right to modify the product

## PicoKom domestic amplifier

1 output: VHF/UHF - LTE790 Ready

Domestic amplifier with 1 output and automatic gain adjustment to extend the terrestrial television home network.

Equipped with LTE790/4G filtering and input power supply for pre-amplifier or BOSS system feeding.

**Ref.560541**

**Art.Nr**

NV241PICOLTE

**EAN13**

8424450166581

### Highlights

- Plug & Play, no adjustments required: equipped with automatic gain regulation, without any impact on signal quality
- Pleasing design and limited size: can be installed in 100 mm x 100 mm connection boxes
- EasyF connection system
- Integrated high-performance switched-mode power supply: reduced power consumption (40% less than a standard amplifier)
- Fully automated manufacturing, subject to the most stringent quality controls

### Main features

- ON/OFF DC pass switch, for pre-amplifier or BOSS system powering
- Easy mounting, preserving the bending radius of the coaxial cables
- Can be wall-mounted using screws

### Discover

#### EasyF connection system: simplicity and savings

EasyF is an innovative connection concept where the inner conductor of the coaxial cable is directly inserted in the device, thus improving connection reliability. Thanks to the absence of F connectors, the chassis can be reduced and the

connection of two cables secured with a a single screw.

- Real time savings: speeding the installation is possible without the need for coaxial cable termination. Furthermore, there is no need for screwing the connectors on the device, which is sometimes difficult when there is little room
- Connection reliability: the clamp holding the cables prevents the coaxial cable to come off
- Cost savings: no additional connectors are required (neither F nor IEC)
- Space optimization: inputs and outputs are always on the same side of the device to prevent coaxial cables from bending, and to make working inside cabinets and register boxes easier
- Very easy three-step mounting: only screwing and unscrewing the covers is required to connect both cables:

1. Unscrew the device's cover to access the connection

2. Insert the previously stripped coaxial cables

3. Close the cover and screw to ensure connection

## Learn more about EasyF system reliability

With EasyF, the connection between the coaxial cable and the device is carried out using an automated system for contact insertion of the inner conductor, without any soldering.

- Always as new: the device's operating life increases when the factor of solder wearing out with time is removed
- Failure rate reduction: usually produced as a result of cold soldering joints
- Electromagnetic behaviour optimization: for high frequencies
- Our commitment with environment is reinforced: pollution caused by the welding process is eliminated and production power consumption is reduced

## Technical specifications

Outputs			1		
Frequency margin		MHz	47...400	470...790	
Gain	G	dB	14	20	
Gain adjustment range			Auto 0...20	Auto 0...20	
Max.output level	EN 50083 IMD3 (2 tones, -35dB)	Vout	dB $\mu$ V	109	113
	DIN45004B			102	106
	2 CH's VHF DVB-T			93	
	10 CH's VHF DVB-T			94	
Noise figure	N.F.	dB	4	5	
Power supply/Max. current inputs	OFF	Vdc/ mA	0/0		
	ON		12/150		
Mains voltage/frequency		V~/Hz	196...253 / 50-60		
AC power consumption		W	3,7		
Through current Out -> In		mA	-		
Protection index		IP	20		
Operating temperature range		°C	-5 ... +45		