



*Televés reserves the right to modify the product*

## "F" Power Supply Unit

24 V - 130 mA, 2 outputs

Domestic 24 V-power supply (130 mA) that powers equipment through the input coaxial cable while allowing the transmission of the TV signal. Included in the installation to power either mast amplifiers or a BOSS system. Furthermore, it is equipped with two outputs.

<b>Ref.5504</b>	Box	
	<b>Art.Nr</b>	NT24F
	<b>EAN13</b>	8424450139400
<b>Ref.550402</b>	Blister	
	<b>Art.Nr</b>	NT24F-B
	<b>EAN13</b>	8424450141885

### Highlights

- High-performance switched-mode power supply: saves up to 40% power consumption
- Low-impact visual design and limited size
- "F" connectors
- Fully automated manufacturing, subject to the most stringent quality controls

### Main features

- Can be wall-mounted using screws
- Through losses may vary depending on whether 1 or 2 outputs are used

## Technical specifications

Frequency margin		MHz	5 - 862
Through loss	1 out	dB	Main: 1,5 typ. / Aux: ---
	2 out		Main: 4 typ. / Aux: 4 typ.
Output Interstage equalizers		V ---	24
Max. output current		mA	130
Min. output current		mA	30
Mains volt.			207-253 V~ 50/60Hz
Consumpt máx.		mA~	35
Protection Level		IP	20
Working temperature		°C	-10 ... +45
Plug type			EU