



Televes förbehåller sig rätten att ändra produkten

SFP-modul LC/PC Coaxdata, även EnGenius

1000Base-X, för 2 fiber

Media adapter med fiberingång, som ansluts till Ethernet-ingången på en CoaxData enhet för att tillåta CoaxData att också kunna anslutas till ett optiskt fibernät.

Ref.769210

Art.Nr

EKASFP2F

EAN13

8424450167175

Står Ut För

- Kontakt LC/PC
- Max 10 km

Huvudegenskaper

- Dessa fungerar också bra till EnGenius-switchar med SFP-ingång.
- Klarar upp till 10 km.

Tekniska specifikationer

Working Ratinas	Units	Min.	Typ.	Max.
Power Supply Voltage	V	3.13	-	3.46
Working Temperature	°C	-20	-	+60
Data Rate	Mbps	-	-	1250
Máximum distance	Km	-	-	10
Optical Transmitter	Units	Min.	Typ.	Max.
Center Wavelength Range	nm	1260	1310	1360
Spectral Width	nm	-	-	4
Differential Input Voltage	mV	500	-	2400
Optical Power Output	dBm	-9	-5	-3
Optical Fall/RiseTime (20%~80%)	ps	-	-	260
TX Disable Output Voltage	V	2.0	-	Vcc
TX Fault Output Voltage	V	2.0	-	Vcc
Optical Receiver	Units	Min.	Typ.	Max.
Differential Output Voltage	mV	400	-	1600
Optical Receiver Sensivity	dBm	-	-	-19
Maximum input optical power	dBm	-3	-	-
Receiver loss of signal (LOS) voltage	V	2	-	-
Signal detect range	dBm	-35	-	-20
Signal detect hysteresis	dB	0.5	-	6

[More about Coaxdata Products](#)