



## Power supply unit 12V - 1.5A (UK)

Device that converts alternating current into direct current to power a multiswitch or an optical converter to RF.

|                     |               |
|---------------------|---------------|
| <b>Ref.</b>         | 732210        |
| <b>Logical ref.</b> | MS-NT1215UK   |
| <b>EAN13</b>        | 8424450175163 |

### Packaging info

|               |         |
|---------------|---------|
| <b>Box</b>    | 1 pcs.  |
| <b>Carton</b> | 10 pcs. |

### Physical data

|                            |          |
|----------------------------|----------|
| <b>Net weight</b>          | 160.00 g |
| <b>Gross weight</b>        | 190.00 g |
| <b>Width</b>               | 49.00 mm |
| <b>Height</b>              | 98.00 mm |
| <b>Depth</b>               | 60.00 mm |
| <b>Main product weight</b> | 160.00 g |

### Highlights

- 18 W maximum power
- Plug-in power supply
- It is recommended not to exceed 65% of the maximum current of the PSU under continuous operating
- Wide range of operating temperatures

- Limited size

Technical specifications : Ref. 732210

|                       |     |               |
|-----------------------|-----|---------------|
| Plug type             |     | UK            |
| Input voltage         | Vac | 100 ... 240   |
| Mains frequency       |     | 50 Hz / 60 Hz |
| Output voltage        | Vdc | 12            |
| Max. output current   | A   | 1.5           |
| Operating temperature | °F  | 23 ... 113    |
| Protection index (IP) |     | 20            |