



Televes reserves the right to modify the product

V Zenit MIX antenna BIII/UHF

Two antennas in one

The V Zenit MIX antenna combines two antennas in one for a mixed reception. The UHF part consists in a V-type structure, formed by two vertically stacked Yagi in phase, which provides an exceptional relation between gain and compactness. Additionally, a dipole and specific reflectors are added for High-VHF reception.

Ref.149381

Art.Nr

EAN13

8424450184455

Highlights

- Quick and secure reflector assembly system
- Robust mechanics with outstanding performance in vibrating situations
- Compact: excellent ratio between gain and length
- Flatness of the frequency response in the UHF band

Discover

- Built with aluminium (corrosion resistant) for a long service life, and in ABS plastic for high weather resistance
- The mast-mounting system utilizes Zamak to provide sturdiness and stability in adverse weather conditions
- Designed and manufactured in Europe, our products undergo the most stringent quality controls
- The connection box includes a balun for impedance matching

Technical specifications

Bands			BIII	UHF	
Frequency range	MHz		174 ... 216	470 ... 698	
Channels			7 ... 13	14 ... 51	
Gain	dBi		8.5	15	
F/B ratio	dB		> 12	> 23	
Wind load (@130Km/h)	N		96		
Wind load (@150Km/h)	N		132		